

11 - **4** - **4** - **01** - **WC1** - **1** - **S114** - **M02** - **C145** - **L01** - **E00** - **B00**

Table Series

Number of Bearings

- 2 - 2 bearing per carriage
- 4 - 4 bearings per carriage

Carriage Length

- 4 - 4 inches

Travel Length (see page C-14)

- 01 - 1 to 45 inches

Waycovers

- WC1 - with waycovers

Carriage Inserts (see pages C-15)

- 1 - English mount
- 2 - Metric mount

Screw Options (see pages C-18 to C-23)

Rolled ball screws

- S001 - .500 x .500 NPL
- S002 - .500 x .500 PL
- S003 - .500 x .500 NPL(T)
- S004 - .500 x .500 PL(T)
- S005 - .625 x .200 NPL
- S006 - .625 x .200 PL
- S007 - .625 x .200 NPL(T)
- S008 - .625 x .200 PL(T)
- S009 - .625 x 1.000 NPL
- S010 - .625 x 1.000 PL
- S011 - .625 x 1.000 NPL(T)
- S012 - .625 x 1.000 PL(T)

Precision ball screws

- S114 - .625 x .200 NPL
- S115 - .625 x .200 PL
- S116 - 16 x 5 NPL
- S117 - 16 x 5 PL
- S118 - 16 x 10 NPL
- S119 - 16 x 10 PL
- S120 - 16 x 16 NPL
- S121 - 16 x 16 PL
- S999 - other

Ground ball screws

- S212 - .625 x .200 PL
- S213 - .625 x .500 PL
- S214 - 16 x 5 PL
- S215 - 16 x 16 PL

Rolled acme screws

- S300 - .625 x .100 NPL
- S301 - .625 x .100 PL
- S302 - .625 x .200 NPL
- S303 - .625 x .200 PL
- S304 - 16 x 4 NPL
- S305 - 16 x 4 PL

Motor Mount (see pages C-15, C-48 & C-49)

- M00 - none
- M01 - hand crank
- M20 to M98 - see Website
- M99 - other
- M02 - NEMA 23 mount (E)
- M03 - NEMA 23 mount (M)
- M04 - NEMA 34 mount (E)
- M05 - NEMA 34 mount (M)
- M06 - NEMA 23 (RH) wrap
- M07 - NEMA 23 (LH) wrap
- M08 - NEMA 34 (RH) wrap
- M09 - NEMA 34 (LH) wrap

Coupling Options (see pages C-42 to C-43)

- C000 - none
- C999 - other
- C020 to C031 - C100
- C040 to C071 - C125
- C125 to C138 - H100
- C145 to C186 - H131
- C187 to C242 - H163
- C400 to C417 - G100
- C425 to C466 - G126
- C470 to C522 - G158

Limit & Home Switches (see pages C-39 to C-41)

- | | | | | | | |
|-------------------|---------------------|------------|------|------|------------|------------|
| L00 - no switches | | Mechanical | Reed | Hall | Prox (NPN) | Prox (PNP) |
| L99 - other | EOT & home switches | L01 | L04 | L07 | L10 | L13 |
| | EOT switches only | L02 | L05 | L08 | L11 | L14 |
| | home switch only | L03 | L06 | L09 | L12 | L15 |

Encoder Options (see page C-51)

- E00 - none
- E01 - rotary (500 lines/rev)
- E02 - rotary (1000 lines/rev)
- E03 - rotary (1270 lines/rev)
- E10 - linear (2500 lines/inch)
- E11 - linear (250 lines/mm)
- E99 - other

Power-off Brakes (see page C-50)

- B00 - none
- B01 - 24 VDC
- B02 - 90 VDC
- B99 - other

- (E) - English Interface
- (LH) - Left Hand
- (M) - Metric Interface
- (NPL) - Non Preloaded
- (PL) - Preloaded
- (RH) - Right Hand
- (T) - Turcite Nut

Specifications subject to change without notice