

**20 06 06 - WC1 - 1 - S013 - M02 - C165 - L01 - E00 - B00**

**Table Series**

**Carriage Length**

**06** - 6 inches      **12** - 12 inches

**Travel Length** (see pages H-6 & H-8)

**06** - 6 to 55 inches

**Waycovers**

**WC0** - with no waycovers    **WC1** - with waycovers

**Carriage Inserts** (see pages H-7 & H-9)

**1** - English mount      **2** - Metric mount

**Screw Options** (see pages H-18 to H-21)

*Rolled ball screws*

**S013** - .750 x .200 NPL  
**S014** - .750 x .200 PL  
**S015** - .750 x .200 NPL(T)  
**S016** - .750 x .200 PL(T)  
**S017** - .750 x .500 NPL  
**S018** - .750 x .500 PL  
**S019** - .750 x .500 NPL(T)  
**S020** - .750 x .500 PL(T)

*Precision ball screws*

**S122** - .750 x .200 NPL  
**S123** - .750 x .200 PL  
**S124** - 20 x 5 NPL  
**S125** - 20 x 5 PL  
**S128** - 20 x 20 NPL  
**S129** - 20 x 20 PL

*Ground ball screws*

**S216** - .750 x .200 PL  
**S217** - .750 x .500 PL  
**S221** - 20 x 5 PL  
**S222** - 20 x 20 PL

*Rolled acme screws*

**S306** - .750 x .100 NPL  
**S307** - .750 x .100 PL  
**S308** - .750 x .200 NPL  
**S309** - .750 x .200 PL

**S999** - other

**Motor Mount** (see pages H-7 & H-9, H-24 to H-25)

**M00** - none

**M01** - hand crank

**M99** - other

**M02** - NEMA 23 mount (E)

**M03** - NEMA 23 mount (M)

**M04** - NEMA 34 mount (E)

**M05** - NEMA 34 mount (M)

**M08** - NEMA 34 (RH) wrap

**M09** - NEMA 34 (LH) wrap

**M10** - NEMA 42 mount (E)

**M11** - NEMA 42 mount (M)

**M12** - NEMA 42 (RH) wrap

**M13** - NEMA 42 (LH) wrap

**Coupling Options** (see pages H-22 to H-23)

**C000** - none

**C999** - other

**C056 to C063** - C125

**C084 to C090** - C150

**C165 to C174** - H131

**C201 to C211** - H163

**C445 to C454** - G126

**C481 to C491** - G158

**Limit & Home Switches** (see pages H-15 to H-17)

**L00** - no switches

**L99** - other

EOT & home switches

EOT switches only

home switch only

Mechanical

**L01**

**L02**

**L03**

Reed

**L04**

**L05**

**L06**

Hall

**L07**

**L08**

**L09**

Prox (NPN)

**L10**

**L11**

**L12**

Prox (PNP)

**L13**

**L14**

**L15**

**Encoder Options** (see page H-27)

**E00** - none

**E01** - rotary (500 lines/rev)

**E02** - rotary (1000 lines/rev)

**E03** - rotary (1270 lines/rev)

**E10** - linear (2500 lines/inch)

**E11** - linear (125 lines/mm)

**E99** - other

**Power-off Brakes** (see page H-26)

**B00** - none

**B03** - 24 VDC

**B04** - 90 VDC

**B99** - other

(E) - English Interface

(LH) - Left Hand

(M) - Metric Interface

(NPL) - Non Preloaded

(PL) - Preloaded

(RH) - Right Hand

(T) - Turcite Nut